

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuartielles <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuartielles <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2     This sketch reads a piezo element to detect a knocking sound.
3     It reads an analog pin and compares the result to a set threshold.
4     If the result is greater than the threshold, it writes
5     "knock" to the serial port, and toggles the LED on pin 13.
6
7     The circuit:
8     * + connection of the piezo attached to analog in 0
9     * - connection of the piezo attached to ground
10    * 1-megohm resistor attached from analog in 0 to ground
11
12    http://www.arduino.cc/en/Tutorial/Knock
13
14    created 25 Mar 2007
15    by David Cuartielles <http://www.0j0.org>
16    modified 30 Aug 2011
17    by Tom Igoe
18
19    This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13;      // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0;      // variable to store the value read from the sensor pin
29  int ledState = LOW;         // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600);      // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2     This sketch reads a piezo element to detect a knocking sound.
3     It reads an analog pin and compares the result to a set threshold.
4     If the result is greater than the threshold, it writes
5     "knock" to the serial port, and toggles the LED on pin 13.
6
7     The circuit:
8     * + connection of the piezo attached to analog in 0
9     * - connection of the piezo attached to ground
10    * 1-megohm resistor attached from analog in 0 to ground
11
12    http://www.arduino.cc/en/Tutorial/Knock
13
14    created 25 Mar 2007
15    by David Cuartielles <http://www.0j0.org>
16    modified 30 Aug 2011
17    by Tom Igoe
18
19    This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13;      // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0;      // variable to store the value read from the sensor pin
29  int ledState = LOW;         // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600);      // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10 * 1-megohm resistor attached from analog in 0 to ground
11
12 http://www.arduino.cc/en/Tutorial/Knock
13
14 created 25 Mar 2007
15 by David Cuartielles <http://www.0j0.org>
16 modified 30 Aug 2011
17 by Tom Igoe
18
19 This example code is in the public domain.
20
21 */
22 // these constants won't change:
23 const int ledPin = 13; // led connected to digital pin 13
24 const int knockSensor = A0; // the piezo is connected to analog pin 0
25 const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27 // these variables will change:
28 int sensorReading = 0; // variable to store the value read from the sensor pin
29 int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31 void setup() {
32   pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33   Serial.begin(9600); // use the serial port
34 }
35
36 void loop() {
37   // read the sensor and store it in the variable sensorReading:
38   sensorReading = analogRead(knockSensor);
39
40   // if the sensor reading is greater than the threshold:
41   if (sensorReading >= threshold) {
42     // toggle the status of the ledPin:
43     ledState = !ledState;
44     // update the LED pin itself:
45     digitalWrite(ledPin, ledState);
46     // send the string "Knock!" back to the computer, followed by newline
47     Serial.println("Knock!");
48   }
49   delay(100); // delay to avoid overloading the serial port buffer
50 }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13;      // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0;      // variable to store the value read from the sensor pin
29  int ledState = LOW;         // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600);      // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10 * 1-megohm resistor attached from analog in 0 to ground
11
12 http://www.arduino.cc/en/Tutorial/Knock
13
14 created 25 Mar 2007
15 by David Cuartielles <http://www.0j0.org>
16 modified 30 Aug 2011
17 by Tom Igoe
18
19 This example code is in the public domain.
20
21 */
22 // these constants won't change:
23 const int ledPin = 13; // led connected to digital pin 13
24 const int knockSensor = A0; // the piezo is connected to analog pin 0
25 const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27 // these variables will change:
28 int sensorReading = 0; // variable to store the value read from the sensor pin
29 int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31 void setup() {
32   pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33   Serial.begin(9600); // use the serial port
34 }
35
36 void loop() {
37   // read the sensor and store it in the variable sensorReading:
38   sensorReading = analogRead(knockSensor);
39
40   // if the sensor reading is greater than the threshold:
41   if (sensorReading >= threshold) {
42     // toggle the status of the ledPin:
43     ledState = !ledState;
44     // update the LED pin itself:
45     digitalWrite(ledPin, ledState);
46     // send the string "Knock!" back to the computer, followed by newline
47     Serial.println("Knock!");
48   }
49   delay(100); // delay to avoid overloading the serial port buffer
50 }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10 * 1-megohm resistor attached from analog in 0 to ground
11
12 http://www.arduino.cc/en/Tutorial/Knock
13
14 created 25 Mar 2007
15 by David Cuatrecasas <http://www.0j0.org>
16 modified 30 Aug 2011
17 by Tom Igoe
18
19 This example code is in the public domain.
20
21 */
22 // these constants won't change:
23 const int ledPin = 13; // led connected to digital pin 13
24 const int knockSensor = A0; // the piezo is connected to analog pin 0
25 const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27 // these variables will change:
28 int sensorReading = 0; // variable to store the value read from the sensor pin
29 int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31 void setup() {
32   pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33   Serial.begin(9600); // use the serial port
34 }
35
36 void loop() {
37   // read the sensor and store it in the variable sensorReading:
38   sensorReading = analogRead(knockSensor);
39
40   // if the sensor reading is greater than the threshold:
41   if (sensorReading >= threshold) {
42     // toggle the status of the ledPin:
43     ledState = !ledState;
44     // update the LED pin itself:
45     digitalWrite(ledPin, ledState);
46     // send the string "Knock!" back to the computer, followed by newline
47     Serial.println("Knock!");
48   }
49   delay(100); // delay to avoid overloading the serial port buffer
50 }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuartielles <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2  This sketch reads a piezo element to detect a knocking sound.
3  It reads an analog pin and compares the result to a set threshold.
4  If the result is greater than the threshold, it writes
5  "knock" to the serial port, and toggles the LED on pin 13.
6
7  The circuit:
8  * + connection of the piezo attached to analog in 0
9  * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuatrecasas <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuartielles <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]

Construção do fluxograma do jogo VelhaBall

Detecção de impacto.

Nosso primeiro problema a resolver, para a construção do programa/sketch-arduino do jogo VelhaBall, será definir como o arduino fará a leitura dos nove sensores (cápsulas piezoelétricas). Esses sensores indicarão em qual painel das matriz a bola bateu.

Para isso, utilizaremos nove portas analógicas de entrada para detectar o sinal vindo da cápsula piezoelétrica. A opção de hardware mais adequada é o Arduino Mega que possui 16 portas analógicas.



Baseado neste modelo e utilizando as portas A0, A1, A2, A3, A4, A5, A6, A7 e A8, escreva o programa que possibilite ao Arduino ler os nove sensores do jogo VelhaBall. Bom trabalho!!!!

```
1  /* Knock Sensor
2   This sketch reads a piezo element to detect a knocking sound.
3   It reads an analog pin and compares the result to a set threshold.
4   If the result is greater than the threshold, it writes
5   "knock" to the serial port, and toggles the LED on pin 13.
6
7   The circuit:
8   * + connection of the piezo attached to analog in 0
9   * - connection of the piezo attached to ground
10  * 1-megohm resistor attached from analog in 0 to ground
11
12  http://www.arduino.cc/en/Tutorial/Knock
13
14  created 25 Mar 2007
15  by David Cuartielles <http://www.0j0.org>
16  modified 30 Aug 2011
17  by Tom Igoe
18
19  This example code is in the public domain.
20
21  */
22  // these constants won't change:
23  const int ledPin = 13; // led connected to digital pin 13
24  const int knockSensor = A0; // the piezo is connected to analog pin 0
25  const int threshold = 100; // threshold value to decide when the detected sound is a knock or not
26
27  // these variables will change:
28  int sensorReading = 0; // variable to store the value read from the sensor pin
29  int ledState = LOW; // variable used to store the last LED status, to toggle the light
30
31  void setup() {
32    pinMode(ledPin, OUTPUT); // declare the ledPin as as OUTPUT
33    Serial.begin(9600); // use the serial port
34  }
35
36  void loop() {
37    // read the sensor and store it in the variable sensorReading:
38    sensorReading = analogRead(knockSensor);
39
40    // if the sensor reading is greater than the threshold:
41    if (sensorReading >= threshold) {
42      // toggle the status of the ledPin:
43      ledState = !ledState;
44      // update the LED pin itself:
45      digitalWrite(ledPin, ledState);
46      // send the string "Knock!" back to the computer, followed by newline
47      Serial.println("Knock!");
48    }
49    delay(100); // delay to avoid overloading the serial port buffer
50  }
51
```

Construção do fluxograma do jogo VelhaBall

Construa seu programa aqui.

[illegible]